



# OPTONICA





## PORTABLE POWER STATION 1000W SKU: 9420

 Camera (16W)  
Around 51 Recharges


 Projector (100W)  
Around 8.3 Hours


 Camping light (125W)  
Around 6.6 Hours

 Macbook 12  
Around 13 Recharges


 Car Fridge (60W)  
Around 13.8 Hours





 Phone (4000mAh)  
Around 70 Recharges

 Rice cooker (330W)  
Around 2.5 Hours

 Electric fan (45W)  
Around 18.4 Hours

 Refrigerator (120W)  
Around 6.9 Hours

 Drone (40W)  
Around 20 Recharges

 Photography lights (300W)  
Around 2.8 Hours

# SPECIFICATIONS

Output		
AC output	Rated voltage	230V
	Rated power	1000W
	Peak power	2000W
	Frequency	50Hz
DC*2 Output	Rated voltage	12V
	Rated current	0-10A
DC Output Ciger Socket	Rated voltage	13.3V
	Rated current	10A
USB-A*3 Output	Rated voltage	5V
	Rated current	2.4A
USB-C*1 Output	PD: 100W Max	5V3A, 9V3A, 12V3A, 15V3A, 20V5A
Floodlight	mlm	200 Low / 800 Middle / 1400 high
Input		
DC Input	Rated voltage	12V-24V(12V 10A)
	Rated power	Max 200W
USB-C*1 Input	PD: 100W Max	5V3A, 9V3A, 12V3A, 15V3A, 20V5A
DC input and USB-C*1 input at the same time to recharge the power station, the input power can be up to 300W max		
Battery		
Rated capacity	1036.8Wh	
Battery cell type	Lithium-ion	
General		
Working environment condition	Relative humidity: 20%-90%	
	Temperature: 32-104°F (-10-40°C)	
Size	332.5*245*255mm±5mm	



**CHARGE FIRST!** Before using your new power station, plug it into a suitable power outlet until it is fully charged. Then you can start your exciting journey with it.