



OPTONICA



PORTABLE POWER STATION 600W SKU: 9419

 Camera (16W)
Around 30 Recharges


 Projector (100W)
Around 5 Hours


 Camping light (125W)
Around 4 Hours

 Macbook 12
Around 7 Recharges


 Car Fridge (60W)
Around 8.3 Hours





 Phone (4000mAh)
Around 42 Recharges

 Rice cooker (330W)
Around 1.5 Hours

 Electric fan (45W)
Around 11.1 Hours

 Refrigerator (120W)
Around 4.1 Hours

 Drone (40W)
Around 12.3 Recharges

 Photography lights (300W)
Around 1.7 Hours

SPECIFICATIONS

Output		
AC output	Rated voltage	230V
	Rated power	600W
	Peak power	1000W
	Frequency	50Hz
DC*2 Output	Rated voltage	13.3V
	Rated current	10A
DC Output Ciger Socket	Rated voltage	13.3V
	Rated current	10A
USB-A*3 Output	Rated voltage	5V
	Rated current	2.4A
USB-C*1 Output	PD: 100W Max	5V3A, 9V3A, 12V3A, 15V3A, 20V5A
Floodlight	mlm	200 Low / 800 Middle / 1400 high
Input		
DC Input	Rated voltage	12V-24V(12V 10A)
	Rated power	Max 120W
USB-C*1 Input	PD: 100W Max	5V3A, 9V3A, 12V3A, 15V3A, 20V5A
DC input and USB-C*1 input at the same time to recharge the power station, the input power can be up to 220W max		
Battery		
Rated capacity	512Wh	
Battery cell type	Lithium-ion	
General		
Working environment condition	Relative humidity: 20%-90%	
	Temperature: 32-104°F (-10-40°C)	
Size	290*210*204mm±5mm	



CHARGE FIRST! Before using your new power station, plug it into a suitable power outlet until it is fully charged. Then you can start your exciting journey with it.